

BUD 140W

FAST CHARGE POWER ADAPTER

GIFTBOX: 8435430626346
EXPORT CARTON: 8435430626353



USB-C
3 PORTS



USB-A
1 PORT



PD3.1 / PPS



QC 3.0



140W
MAX OUTPUT
POWER



FOR
LAPTOP / MAC



FOR TABLET /
SMARTPHONE



FOR
HEADPHONE



FOR
SPEAKER



DESCRIPTION

- Wall charger with 3 USB-C ports (PD3.1 & PPS) and 1 USB-A QC3.0 port with a maximum power output of 140W.
- Made of GaN and fireproof materials, it's the ideal charger for smartphones, tablets, and laptops.
- It's a smart charger that will allow more efficient charging of the device's battery, thus extending its lifespan.
- Additionally, thanks to its advanced PD3.1 technology, it supports 140W power output through several of its USB-C ports.

MAIN CHARACTERISTICS

- Input: 100-240V~50/60Hz, 1.8A
- Output:
 - USB-C1: 3.3V-21V/5A; 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A, 28V/5A
 - USB-C2: 3.3V-21V/5A; 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A, 28V/5A
 - USB-C3: 3.3V-11V/5A; 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3.25A
 - USB-A: 4.5V/5A, 5V/4.5A, 5V/3A, 9V/3A, 12V/2.5A, 20V/1.5A
 - USB-C1+USB-C2/C3: 100W+35W
 - USB-C1/C2+USB-A: 100W+30W
 - USB-C2+USB-C3: 100W+35W
 - USB-C3+USB-A: 15W (5V3A)
 - USB-C1+USB-C2+USB-C3: 65W+45W+30W
 - USB-C1+USB-C2+USB-A: 65W+45W+30W
 - USB-C1/C2+USB-C3+USB-A: 100W+15W (C3+A)
 - USB-C1+USB-C2+USB-C3+USB-A: 65W+45W+15W (C3+A)
- Total Output Power: 140W

PACKAGE CONTENTS

- BUD 140W
- Installation guide

LOGISTIC DATA

Dimensions (mm)
and weight (g)

	W	D	H	⚖
- External box:	205	182	195	-
- Package:	91	33	154	-
- Product:	29	124	61	256
- Units per pallet:	1360			
- Units per box:	10			
- Boxes per pallet:	136			
- Boxes on base:	17			
- Boxes in height:	8			