

BUD 165W

FAST CHARGE POWER ADAPTER

GIFTBOX: 8435430626360
EXPORT CARTON: 8435430626377



USB-C
3 PORTS



USB-A
1 PORT



PD3.1 / PPS



QC 3.0



165W
MAX OUTPUT
POWER



FOR
LAPTOP / MAC



FOR TABLET /
SMARTPHONE



FOR
HEADPHONE



FOR
SPEAKER



DESCRIPTION

- Wall charger with 3 USB-C ports (PD3.1 & PPS) and 1 USB-A QC3.0 port with a maximum power output of 165W.
- Made of GaN and fireproof materials, it's the ideal charger for smartphones, tablets, and laptops.
- It's a smart charger that will allow more efficient charging of the device's battery, thus extending its lifespan.
- Additionally, thanks to its advanced PD3.1 technology, it allows for a power output of 140W through its USB-C1 port.

MAIN CHARACTERISTICS

- Input: 100-240V~50/60Hz, 2.3A Max
- Output:
 - USB-C1: PPS: 3.3V-21V/5A
 - PD: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A, 28V/5A (Max 140W)
 - USB-C2: PPS: 3.3V-21V/5A
 - PD: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A (Max 100W)
 - USB-C3: PPS 3.3V-11V/5A
 - PD: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3.25A (Max 65W)
 - USB-A: 5V/3A, 9V/3A, 12V/2.5A, 20V/1.5A (Max 30W)
 - USB-C1+USB-C2/C3: 100W+65W
 - USB-C1/C2+USB-A: 100W+30W
 - USB-C2+USB-C3: 100W+65W
 - USB-C3+USB-A: 15W (5V/3A)
 - USB-C1+USB-C2+USB-C3: 65W+65W+30W
 - USB-C1+USB-C2+USBA: 65W+65W+30W
 - USB-C1/C2+USB-C3+USBA: 100W+15W (5V/3A)
 - USB-C1 65W+USB-C2 65W+USB-C3+USB-A: 15W (5V/3A)
- Total Output Power: 165W

PACKAGE CONTENTS

- BUD 165W
- Installation guide

LOGISTIC DATA

Dimensions (mm)
and weight (g)

	W	D	H	
- External box:	225	215	180	-
- Package:	102	40	140	-
- Product:	35	110	72	250
- Units per pallet:	1200			
- Units per box:	10			
- Boxes per pallet:	120			
- Boxes on base:	15			
- Boxes in height:	8			