

BUD 240W

FAST CHARGE POWER ADAPTER

GIFTBOX: 8435430626384
EXPORT CARTON: 8435430626391



USB-C
3 PORTS



USB-A
1 PORT



PD3.1 / PPS



QC 3.0



240W
MAX OUTPUT
POWER



FOR
LAPTOP / MAC



FOR TABLET /
SMARTPHONE



FOR
HEADPHONE



FOR
SPEAKER



DESCRIPTION

- Wall charger with 3 USB-C ports (PD3.1 & PPS) and 1 USB-A QC3.0 port with a maximum power output of 240W.
- Made of GaN and fireproof materials, it's the ideal charger for smartphones, tablets, and laptops.
- It's a smart charger that will allow more efficient charging of the device's battery, thus extending its lifespan.
- Additionally, thanks to its advanced PD3.1 technology, it allows for a power output of 140W through its USB-C1 port.

MAIN CHARACTERISTICS

- Input: 100-240V~50/60Hz, 2.8A
- Output:
 - USB-C1 (140W): PPS: 3.3V-21V/5A
PD: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A, 28V/5A
 - USB-C2 (100W): PPS: 3.3V-21V/5A
PD: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A
 - USB-C3 (65W): PPS: 3.3-11V/5A
PD: 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/3.25A
 - USB-A (60W): 4.5V/5A, 5V/4.5A, 5V/3A, 9V/3A, 12V/3A, 20V/3A
 - USB-C1+USB-C2: 140W+100W
 - USB-C1+USB-C3: 140W+65W
 - USB-C2+USB-C3: 65W+35W
 - USB-C1+USB-A: 140W+60W
 - USB-C2+USB-A: 65W+30W
 - USB-C3+USB-A: 24W (5V/2.4A+5V/2.4A)
 - USB-C1+USB-C2+USB-C3: 140W+65W+35W
 - USB-C1+USB-C2+USB-A: 140W+65W+30W
 - USB-C1+USB-C3+USB-A:
140W+12W (5V/2.4A)+12W (5V/2.4A)
 - USB-C2+USB-C3+USB-A:
65W+12W (5V/2.4A)+12W (5V/2.4A)
 - USB-C1+USB-C2+USB-C3+USB-A:
140W+65W+12W (5V/2.4A)+12W (5V/2.4A)
- Total Output Power: 240W

PACKAGE CONTENTS

- BUD 240W
- Installation guide

LOGISTIC DATA

Dimensions (mm)
and weight (g)

	W	D	H	⚖
- External box:	225	210	200	-
- Package:	95	40	159	-
- Product:	36	129	65	424
- Units per pallet:	1200			
- Units per box:	10			
- Boxes per pallet:	120			
- Boxes on base:	15			
- Boxes in height:	8			